

Broadband Capacitors Cross Reference Chart



Case Size	PPI Part Number	KAVX	Frequency Range	I.L.	WVDC	Size (inches)	Value
01005BB	01005BB104MW4R0	N/A	16kHz - >67GHz	<1dB	4V	.010 x .005	100,000pF (100nF)
	01005BB104MW6R3	550W	16kHz - >67GHz	<1dB	6.3V	.010 x .005	100,000pF (100nF)
	01005BB104MW100	N/A	16kHz - >67GHz	<1dB	10V	.010 x .005	100,000pF (100nF)
0201BB	0201BB103KW250**	550Z	160kHz - >32GHz	<1dB	25V	.020 x .010	10,000pF (10nF)
	0201BB104KW160**	560Z	16kHz - >40GHz	<1dB	16V	.020 x .010	100,000pF (100nF)
0402BB	0402BB103KW500	520L	160kHz - >40GHz	<1dB	50V	.040 x .020	10,000pF (10nF)
	0402BB104KW500**	N/A	16kHz - >50GHz	<1.2dB	50V	.040 x .020	100,000pF (100nF)
0603BB	0603BB104KW101**	550S	16kHz - >20GHz	<1.2dB	100V	.060 x .030	100,000pF (100nF)
0805BB	0805BB103KW101**	N/A	160kHz - >3GHz	<.25dB	100V	.080 x .050	10,000pF (10nF)